



## EXPANSION CONTENT

This free wavetable expansion for the Crumar Seven features the sampling of a Petrof P-173 “Breeze”, a very nice grand piano built by Petrof in the Czech Republic.

We borrowed this piano in spring 2021 by our piano partner in Italy, the music shop “Bettin” located in Padova, because we needed a small piano to test our auto-sampling robot. We actually did not choose this exact model, we just wanted a decent piano for our testing, but, to our surprise, this piano was so fascinating, detailed, precise, and had this brilliant yet sweet sound that, once we got our robot set up properly, we decided to repeat some extra sampling sessions to have our samples done at production level quality.

The result is a multi-sample consisting in 182 high quality stereo samples spread over 3 to 5 velocity layers for a total of 369 MB worth of Petrof sound.

Once loaded into the Seven, the GSP-01 sample playback engine adds a layer of *physically modeled resonances* that enrich the sound by adding the missing interactions between notes that naturally happen when playing a piano but can't be reproduced just with samples.

## INSTALLING THE SAMPLE CONTENT

First thing: make sure you have the latest firmware installed.  
This expansion requires firmware version 1.30 or greater.

DO NOT ATTEMPT TO INSTALL THIS EXPANSION ON AN OLDER FIRMWARE. Chances are that the installation will fail or, in the worst scenario, your Seven sample memory may be corrupted.

If you're unsure, go the Crumar website and check the Support section.

Copy all the content of the folder **VeniceGrandBreeze** onto the root of a blank USB Memory Stick, then safely remove the USB Memory from your computer and connect it to the **SYSTEM USB** port of your Seven. Connect to the Seven Editor and go to the Editor's home page, then click/tap the **INSTALL NEW** button that you find in the **WAVETABLE EXPANSIONS** section.

**BEWARE:** The installation may take up to 25~30 seconds, during which the interface shows a "please wait" screen. Just wait, don't quit the editor, don't extract the USB memory, don't click/tap any link, and don't play the instrument. At the end of the process the editor page should automatically reload.

## HOW TO FIND THE NEW SAMPLE CONTENT

Go to the **SELECT PIANO** page of the Editor. The new sample content is appended at the bottom of the list. In case you don't find it, try to reload the editor page. Of course, it is possible to use this content to create your own sounds.

[www.Crumar.it](http://www.Crumar.it)

*Any trademarks mentioned in this document are used only for reference purposes.  
Registered trademarks belong to their respective owners.*